

Junior Plus



- 2, 4, 6, 8 stations
- 2 independent programs
- 3 starts per program
- Water Budget: from 10% to 200%

The Junior Plus controller is ideal for watering small gardens and not very big areas where flexible irrigation and simple programming is required. Junior Plus is the right compromise for anyone who needs to manage irrigation in his/her garden without a controller that is too complicated to program.



Features

- Irrigation duration from 1 minute to 599 minutes (10 hours), with 1 minute increases
- Irrigation programming:
 - Weekly irrigation
 - Irrigation on alternate days from 1 to 30 days
- Program cancellation possibility
- Stacking Program
- Rain interruption function
- Manual start per program or per station
- Pump control
- EC approvals



Additional Features

“24V” warning indicating a power cut

“25V” warning indicating a burnt fuse

Specifications

Input power:

- 2 AA 1,5 V alkaline batteries (not included)

Output power:

- Max output per station: 24 VAC (0,35 A)
- Max output per valve (including pump control): 24VAC (0,5 A)

0,5 Amp fuse

Dimensions

Height: 9,5 cm

Width: 11,5 cm

Depth: 2,5 cm

Options

Rain sensor

Codification

| Code | Description |
|-----------------|--|
| JR+2-220 | Junior Plus, 2-station controller, with external transformer 220 VAC |
| JR+4-220 | Junior Plus, 4-station controller, with external transformer 220 VAC |
| JR+6-220 | Junior Plus, 6-station controller, with external transformer 220 VAC |
| JR+8-220 | Junior Plus, 8-station controller, with external transformer 220 VAC |